# **Product datasheet**

Specifications



# LED bulb, Harmony XB4, BA9s, green, 48V AC/DC

#### Main

Range Compatibility	Harmony XB4
Accessory / Separate Part Type	LED bulb
Accessory / Separate Part Category	Lighting accessory
Accessory / Separate Part Destination	Illuminated push-button
[Us] Rated Supply Voltage	48 V AC/DC
Signalling Colour	Green
Sale Per Indivisible Quantity	1

DL1CJ0483

### Complementary

Bulb Base	BA 9s
Net Weight	0.002 kg

### **Packing Units**

<u> </u>	
Unit Type Of Package 1	PCE
Number Of Units In Package 1	1
Package 1 Height	1.0 cm
Package 1 Width	1.0 cm
Package 1 Length	2.5 cm
Package 1 Weight	2.0 g
Unit Type Of Package 2	BB1
Number Of Units In Package 2	10
Package 2 Height	3.5 cm
Package 2 Width	4.5 cm
Package 2 Length	11.0 cm
Package 2 Weight	28.0 g
Unit Type Of Package 3	S01
Number Of Units In Package 3	200
Package 3 Height	15.0 cm
Package 3 Width	15.0 cm
Package 3 Length	40.0 cm
Package 3 Weight	790.0 g

# **Contractual warranty**

Warranty

18 months

# Sustainability Screen Premium

**Green Premium<sup>TM</sup> label** is Schneider Electric's commitment to delivering products with best-inclass environmental performance. Green Premium promises compliance with the latest regulations, transparency on environmental impacts, as well as circular and low-CO<sub>2</sub> products.

**Guide to assessing product sustainability** is a white paper that clarifies global eco-label standards and how to interpret environmental declarations.

Learn more about Green Premium >

Guide to assess a product's sustainability >



Transparency RoHS/REACh

#### Well-being performance

Reach Free Of Svhc

Rohs Exemption Information Yes

#### **Certifications & Standards**

Reach Regulation	REACh Declaration
Eu Rohs Directive	Pro-active compliance (Product out of EU RoHS legal scope) EU RoHS Declaration
China Rohs Regulation	China RoHS declaration
Environmental Disclosure	Product Environmental Profile
Weee	The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins
Circularity Profile	End of Life Information